

CF Corpo Collare



CF Clamp Body

CF Cuerpo de Abrazadera

Coppia di semicollari

Two clamps halves

Parejas de medias abrazaderas





| Code | Outside diameter ØD1/ØD2 | | Nominal bore pipe (in) | L1 (mm/in) | L2 (mm/in) | H (mm/in) | S (mm/in) | Width (mm/in) |
|--------------------|--------------------------|--------|---------------------------|----------------|---------------|---------------|---------------|------------------|
| | (mm) | (in) | | | | | | |
| CF1-006/006-PP | 6 | | | 36 (1.42") | 20 (.79") | 27 (1.06") | 0,6 (.02") | 30 (1.18") |
| CF1-006.4/006.4-PP | 6,4 | 1/4" | | 36 (1.42") | 20 (.79") | 27 (1.06") | 0,6 (.02") | 30 (1.18") |
| CF1-008/008-PP | 8 | 5/16" | | 36 (1.42") | 20 (.79") | 27 (1.06") | 0,6 (.02") | 30 (1.18") |
| CF1-009.5/009.5-PP | 9,5 | 3/8" | | 36 (1.42") | 20 (.79") | 27 (1.06") | 0,6 (.02") | 30 (1.18") |
| CF1-010/010-PP | 10 | | 1/8" | 36 (1.42") | 20 (.79") | 27 (1.06") | 0,6 (.02") | 30 (1.18") |
| CF1-012/012-PP | 12 | | | 36 (1.42") | 20 (.79") | 27 (1.06") | 0,6 (.02") | 30 (1.18") |
| CF1-012.7/012.7-PP | 12,7 | 1/2" | | 36 (1.42") | 20 (.79") | 27 (1.06") | 0,6 (.02") | 30 (1.18") |
| CF2-012/012-PP | 12 | | | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF2-012.7/012.7-PP | 12,7 | 1/2" | | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF2-013.5/013.5-PP | 13,5 | | 1/4" | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF2-014/014-PP | 14 | | | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF2-015/015-PP | 15 | | | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF2-016/016-PP | 16 | 5/8" | | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF2-017.2/017.2-PP | 17,2 | | 3/8" | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF2-018/018-PP | 18 | | | 53 (2.09") | 29 (1.14") | 27 (1.06") | 0,8 (.03") | 30 (1.18") |
| CF3-019/019-PP | 19 | 3/4" | | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF3-020/020-PP | 20 | | | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF3-021.3/021.3-PP | 21,3 | | 1/2" | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF3-022/022-PP | 22 | 7/8" | | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF3-023/023-PP | 23 | | | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF3-024/024-PP | 24 | | | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF3-025/025-PP | 25 | | | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF3-025.4/025.4-PP | 25,4 | 1" | | 67 (2.64") | 36 (1.42") | 37 (1.46") | 1 (.04") | 30 (1.18") |
| CF4-026/026-PP | 26 | | | 81 (3.19") | 45 (1.77") | 42 (1.65") | 1 (.04") | 30 (1.18") |
| CF4-026.9/026.9-PP | 26,9 | | 3/4" | 81 (3.19") | 45 (1.77") | 42 (1.65") | 1 (.04") | 30 (1.18") |
| CF4-028/028-PP | 28 | | | 81 (3.19") | 45 (1.77") | 42 (1.65") | 1 (.04") | 30 (1.18") |
| CF4-030/030-PP | 30 | | | 81 (3.19") | 45 (1.77") | 42 (1.65") | 1 (.04") | 30 (1.18") |
| CF5-032/032-PP | 32 | 1.1/4" | | 106 (4.17") | 56 (2.20") | 53 (2.09") | 1,2 (.05") | 30 (1.18") |
| CF5-033.7/033.7-PP | 33,7 | | 1" | 106 (4.17") | 56 (2.20") | 53 (2.09") | 1,2 (.05") | 30 (1.18") |
| CF5-035/035-PP | 35 | | | 106 (4.17") | 56 (2.20") | 53 (2.09") | 1,2 (.05") | 30 (1.18") |
| CF5-038/038-PP | 38 | 1.1/2" | | 106 (4.17") | 56 (2.20") | 53 (2.09") | 1,2 (.05") | 30 (1.18") |
| CF5-040/040-PP | 40 | | | 106 (4.17") | 56 (2.20") | 53 (2.09") | 1,2 (.05") | 30 (1.18") |
| CF5-042.4/042.4-PP | 42,4 | | 1.1/4" | 106 (4.17") | 56 (2.20") | 53 (2.09") | 1,2 (.05") | 30 (1.18") |

P CF Piastra a saldare singola

P CF Single weld plate

P CF Placa para soldar simple



| Code | L (mm/in) | B (mm/in) | S (mm/in) | H (mm/in) | ØD (mm/in) | Thread D |
|------------|----------------|---------------|--------------|---------------|---------------|---------------------|
| PINFCF1-M2 | 37 (1.46") | 30 (1.18") | 3 (.12") | 6,5 (.26") | 12 (.47") | M6 (1/4-20 UNC) |
| PINFCF2-M2 | 55 (2.17") | 30 (1.18") | 5 (.20") | 6 (.24") | 14 (.55") | M8 (5/16-18 UNC) |
| PINFCF3-M2 | 70 (2.76") | 30 (1.18") | 5 (.20") | 6 (.24") | 14 (.55") | M8 (5/16-18 UNC) |
| PINFCF4-M2 | 85 (3.35") | 30 (1.18") | 5 (.20") | 6 (.24") | 14 (.55") | M8 (5/16-18 UNC) |
| PINFCF5-M2 | 110 (4.33") | 30 (1.18") | 5 (.20") | 6 (.24") | 14 (.55") | M8 (5/16-18 UNC) |

Disponibile su richiesta la versione precedente senza bugnatura antirotazione


Previous version without anti-rotation embossing available on request

Versión anterior sin relieve antirrotación disponible bajo pedido

PS CF Piastra superiore

PS CF Upper plate

PS CF Placa superior



| Code | L (mm/in) | B (mm/in) | H (mm/in) | S (mm/in) | ØD (mm/in) |
|------------|------------------|---------------|--------------|--------------|---------------|
| PSUPCF1-M3 | 34,5 (1.35") | 30 (1.18") | 7 (.28") | 3 (.12") | 7 (.28") |
| PSUPCF2-M3 | 52 (2.05") | 30 (1.18") | 7 (.28") | 3 (.12") | 9 (.35") |
| PSUPCF3-M3 | 64 (2.51") | 30 (1.18") | 7 (.28") | 3 (.12") | 9 (.35") |
| PSUPCF4-M3 | 79 (3.11") | 30 (1.18") | 7 (.28") | 3 (.12") | 9 (.35") |
| PSUPCF5-M3 | 102,5 (4.03") | 30 (1.18") | 7 (.28") | 3 (.12") | 9 (.35") |

TER CF Vite a testa esagonale

TER CF Hexagon head bolt


TER CF Tornillo de cabeza hexagonal

ISO 4014/4017

Da utilizzare con rondella piana RP CF

To be used with flat washer RP CF

Para uso con la arandela plana RP CF



| Code | Clamp reference | Thread D x L |
|-------------|-----------------|--------------------------------|
| TE-M6X30-M3 | CF1 - CF1L | M6x30 (1/4-20 UNCx1.1/4") |
| TE-M8X30-M3 | CF2 - CF2L | M8x30 (5/16-18 UNCx1.1/4") |
| TE-M8X40-M3 | CF3 - CF3L | M8x40 (5/16-18 UNCx1.1/2") |
| TE-M8X45-M3 | CF4 - CF4L | M8x45 (5/16-18 UNCx1.7/8") |
| TE-M8X55-M3 | CF5 - CF5L | M8x55 (5/16-18 UNCx2.3/16") |

